

## A22 Heater Ohm Measurements

This procedure will help to determine if the heater element is defective on the A22 Lane Machine.

### Step 1

From the operator's side of the lane machine locate and disconnect the heater connection. (Refer to Figure 1)

### Step 2

Using a digital voltage meter set the meter to the ohm setting, probe the two male pins of the heater connector.

74 +/- 6 Ohms for 115V A22

260 +/- 15 Ohms for 230v A22

**Note:** The photos below are for a 115 volt lane machine.

(Figure 1)



(Figure 2)

